

### VMP Motor - Head Performance

Head Specifications					VMP TURBO	
Diameter inches	Length inches	Weight pounds	Unbalance lb-in	Ave Amp (Peak-to-Peak)	Speed <sup>4</sup> rpm	Force pounds
7/8	11.94	1.4	0.029	0.041	<b>13,000</b>	<b>139</b>
<b>1</b>	12.45	2.1	0.029	0.028	<b>13,000</b>	<b>139</b>
<b>1 1/4</b>	12.19	3.0	0.092	0.062	<b>12,500</b>	<b>408</b>
<b>1 1/2</b>	12.04	4.1	0.162	0.079	<b>12,500</b>	<b>719</b>
<b>1 3/4</b>	13.05	6.2	0.236	0.077	<b>12,000</b>	<b>965</b>
<b>2 1/8</b>	13.01	9.2	0.337	0.073	<b>12,000</b>	<b>1,378</b>
<b>2 1/2</b>	12.52	12.2	0.478	0.078	<b>12,000</b>	<b>1,955</b>
Special Purpose Heads						
<b>7/8 Low Force</b>	9.94	1.2	0.012	0.021	<b>13,500</b>	<b>62</b>
<b>2 1/8 Shallow Pour</b>	5.84	3.3	0.168	0.102	<b>12,800</b>	<b>782</b>
<b>Unshaded</b>	Best Performance.					
<b>Shaded</b>	Reduced Performance because speed is too high or too low. <b>A 10% increase in speed reduces the head bearing life by 50%.</b>					
<p><sup>1</sup> The speed provided above is an approximation of the head speed in concrete for the specified motor-head combination. The actual speed will vary depending on temperature, consistency of the concrete, the degree of brush wear, the hours on the bearings, etc. Running an electric motor with too large a head will slow the motor and can result in excess amp draw and heat generation with premature motor failure."</p>						
<p><sup>4</sup> The speed provided above is an approximation of the head speed in concrete with the VMP TURBO Pneumatic Power Unit with the control valve set for the appropriate head size. The actual speed will vary depending on temperature, consistency of the concrete the hours on the bearings, etc.</p>						