

## 12 & 24 Volt DC Quiet Thunder<sup>®</sup> Electric Vibrators Performance Data

Vibrator Model	Unbalance			Speed	Force			Voltage	Amp Draw
	Min	Med	Max		Min	Med	Max		
	lb-in	lb-in	lb-in	rpm	lb	lb	lb	Volts	Amps
	kg-mm	kg-mm	kg-mm		kN	kN	kN		
<b>CEG-400-12</b>	N/A	N/A	0.55	5400	N/A	N/A	455	12V DC	25
			6				2.03		
<b>CEG-800-12</b>	N/A	N/A	1.02	5400	N/A	N/A	845	12V DC	25
			12				3.76		
<b>CEG-1200-12</b>	N/A	N/A	1.41	5400	N/A	N/A	1168	12V DC	25
			16				5.19		
<b>CEG-400-24</b>	N/A	N/A	0.55	5400	N/A	N/A	455	24V DC	10
			6				2.03		
<b>CEG-800-24</b>	N/A	N/A	1.02	5400	N/A	N/A	845	24V DC	10
			12				3.76		
<b>CEG-1200-24</b>	N/A	N/A	1.41	5400	N/A	N/A	1168	24V DC	10
			16				5.19		
<b>CEG-1800-12</b>	1.50	2.00	2.50	5000	1065	1420	1775	12V DC	60
	17	23	29		4.74	6.32	7.90		
<b>CEG-2200-12</b>	2.00	2.50	3.00	5000	1420	1775	2130	12V DC	60
	23	29	35		6.32	7.90	9.47		
<b>CEG-2800-12</b>	2.50	3.00	4.00	5000	1775	2130	2840	12V DC	60
	29	35	46		7.90	9.47	12.63		
<b>CEG-3600-12</b>	3.00	4.00	5.00	5000	2130	2840	3550	12V DC	60
	35	46	58		9.47	12.63	15.79		
<b>CEG-4200-12</b>	4.00	5.00	5.89	5000	2840	3550	4182	12V DC	60
	46	58	68		12.63	15.79	18.60		